

Frequently Asked Questions

What's the advantage of Lync?

Mobility. It's like Skype fully integrated with the phone system. Install Lync on your PC/laptop/smartphone and place calls anywhere you have access to WiFi network

How to reset PIN code or check status of Lync account

<http://cern.ch/resources>->List services->Lync IP Service

How to call Geneva, Switzerland or another country

Geneva: 022xxxxx, France: 0033xxxxxx, etc.

I can not call external numbers

Ask for rights, send a "Phone request", type "Fixed telephone line modification" from <http://edh.cern.ch>

Do I need special devices to use Lync on laptop?

No, you can use your headset or built-in speakers/micro

Where can I use my CERN work number

Anywhere: CERN, home, conference, hotel. You can use Lync application on laptop or smartphone.

Ensure that you have WiFi connection

How to access voice mailbox and configure greetings

Press Menu -> Unlock -> Press "1" key for 3 seconds

How I can add a picture to my Lync profile

Login to <http://social.cern.ch> -> Edit your profile -> Upload a picture and mark "Set Social picture as source for Outlook and Lync"

Tips and Tricks



Configure forwarding/simultaneous call

Press **Unlock** -> Call forwarding ->

-> Choose a CERN number

Search for a person by name

Click **Unlock** -> Type the name of a person. To search for "ANNA" press keys: 2662; 2 for "A", 6 for "N", 6 for "N", 2 for "A".

Put a call on hold

Press **Hold** button (visible once you are in a call)

Transfer an ongoing call

Press **Menu** -> **Unlock** -> Choose "Transfer directly to" or "Consult then Transfer to ...". -> Specify a number or a person name

How to do a factory reset of the phone

Unplug the power. Press simultaneously: wildcard * key, and hash # key, and plug the power. The phone asks for the confirmation before the factory reset

Configuration of Lync IP Phone

Lync IP Phone HP 4120



You can ask service-desk@cern.ch for help to install the device

Info: <http://cern.ch/lync>

To ask questions: <http://cern.ch/lync-community>

Need help? E-mail: service-desk@cern.ch, tel: 77777



Register your phone on the network

Go to Resources portal <https://cern.ch/resources>

Click: Services ->Lync IP Phone service->Register Phone



The screenshot shows a web form titled "Lync IP Phone Service" with a sub-header "Lync IP enhanced telephony". The form is divided into sections: "Service Information", "Settings", and "Register Phone". Under "Register Phone", there are fields for "Model:" (set to "HP 4120"), "MAC Address:", "Office:" (set to "31 R-017"), "Network Outlet:" (a dropdown menu with "[Select an Outlet already connected]"), and "Or enter a free outlet ID:". A note below the MAC field states: "The MAC address can be found on the sticker located under the IP Phone device."

Note: If you have not subscribed to the Lync service follow the EDH Phone request form (link accessible on Resources portal)

Select your model and specify MAC address

Note: MAC address can be found at the back of phone



Select the network outlet you wish to connect the phone to.


Submit the request.

Once the registration has been completed you will receive a confirmation e-mail from the network team.

Connect your phone

Connect the cables

Connect the power and network to your phone




Lan: network cable from a network outlet

PC: network cable connected to your PC/MAC

USB: cable plugged to a Windows PC (optional)

Handset: cable plugged to the handset

Wait for the "Welcome screen"



Start using the phone

Login to the phone system

If there is a user already logged on the phone then perform a factory reset (see Tips section)

1. Press the OK button on the Welcome screen and follow the steps on screen

Note: If you have a Windows PC then confirm availability of a computer

- Lync on Windows will ask you for your credentials

2. Specify the extension number (e.g 77112) and PIN that you have received in the activation e-mail of Lync Phone system

Configure the PIN to LOCK phone

3. Provide a new six digit code to protect your phone Each phone is locked automatically after few minutes of inactivity to prevent other people to access personal information (Lync contacts, call logs etc.)

Configure the time zone

4. Select "GMT +01::00 Amsterdam, Berlin, Bern"

Configuration is finished!