USER'S GUIDE HUAWEI E180 BROADBAND USB KEY (SUNRISE) WITH CERN SWISSCOM SIM CARD



O.S. required: Windows Vista, Windows 7

1) Power on your PC if not yet done and insert your SIM card in the dedicated slot of the BROADBAND USB KEY

2) Plug the device in the USB port of the PC (the light should be blinking green twice every 3seconds).

3) The Operating System automatically detects and recognizes the new hardware and starts the installation wizard:





4) Follow the on-screen instructions of the installation wizard.

<u>Note:</u> If the auto-run program does not start automatically, execute manually the file **AutoRun.exe** (Type: Application) locate on the BROADBAND USB KEY:

🚱 🕞 – 🕃 🕨 Computer 🔸 CD I	Drive (E:) Mobile Partner 🕨	👻 🍫 Search C	D Drive (E:) Mobile Po	ntner 🔎
Organize	Burn			
🛚 🔆 Favorites	Name	Date modified	Туре	Size
🧮 Desktop	🌗 Mobile Partner	16/04/2009 14:35	File folder	
鷆 Downloads	AutoRun	20/01/2009 18:22	Application	124 k
🕮 Recent Places	autorun	07/11/2007 16:41	Setup Information	1 k
	DataCard_Setup	20/01/2009 18:22	Application	124 k
4 🥽 Libraries	DataCard_Setup64	20/01/2009 18:21	Application	173 k
Documents	ResetDevice	19/02/2008 22:16	Application	7 k
🖻 🎝 Music	🕄 Startup	20/01/2007 11:33	Icon	5 k
Pictures	SysConfig.dat	14/04/2009 19:25	DAT File	2 k
 Videos Image: Computer System (C:) O CD Drive (E:) Mobile Partner Network 				
8 items	٠ [m		Þ

5) When the program Mobile Partner is installed, the shortcut icon for the management program appears on the desktop.

6) Start the management program "Mobile Partner", the following window appears:

😨 Mobile Partner		
<u>File Operation T</u> ools <u>H</u> elp		
Connection 🛄 Statistics	: 室 Text 🔽 Phonebook	Sunrise
Profile Name: Sunrise	Verify PIN Current PIN: ***** Remaining attempt(s): 3 OK Cancel	Connect
T	0	

7) Enter the PIN code associated to the SIM card.

8) In order to change the configuration profile from Sunrise to Swisscom, go to: **Tools -> Options -> Profile Management -> New**

Profile Name: Swisscom APN: - Static gprs-swisscom.ch

 gprs.swisscom.ch 		
User name:	leave empty	
Password:	leave empty	
Access number:	*99#	

 General Text Message 	Dial-Up	
 Profile Management Network 	Swisscom	New
	APN	Delete
	ODynamic Static	Edit
	APN: gprs.sw	isscom.ch <u>S</u> ave
	Authentication Access number: *99#	
	Password:	Set as Default
	Advan	ced

9) Please click on the **Advanced** button and proceed to *untick* all the authentication protocols:

Advanced	
IP Settings	
Authentication Protocol Settings	

Click on: Save, then: Set as default and: Connect

10) The connection is ready for use (the light is fixed).